



TOUCH THE DIFFERENCE

Standard USB-C Hub with extended I/O
for AURES YUNO, JAZZ, TWIST and Wincor
iPOS


HUB-RETAIL-KL20
Product Manual



Standard USB-C Hub



3-in-1 Cable
(Power + LAN + USB)
(Optional)



USB-C Cable
(Optional)



180W Power Adapter
and Power Cord



Mounting Bracket



USB-C Hold Bracket



Product Manual
Product Manual



Specifications

| | Model | Standard USB-C Hub |
|---------------|------------------------------|--|
| Front Side | LED | Green when 180W power supply is connected |
| | 24V DC Input | 4-pin 24V DC input with lock connector x 1 |
| | 24V DC Output | 3-pin with lock connector for thermal printer x 1 |
| | 24V PoweredUSB port | Max. 2A / port x 1 |
| | 12V PoweredUSB port | Max. 1.25A / port x 4 |
| | DB9 port | RS232 COM A / COM B / COM C / COM D |
| | LAN port | 10/100/1000 Base-T x 1 (1) Under YUNO POS / Wincor iPOS configuration, only USB 2.0 x 4 and LAN-A can be used. (2) Under JAZZ / TWIST POS configuration, USB 2.0 x 4, USB 3.0 x 2 and LAN-B can be used. *LAN-A can't be used! |
| | USB port | USB 2.0 x 4 & USB 3.0 x 2 |
| | Cash Drawer port | 24 / 12 V Cash Drawer x 1 |
| | Cable Clamp | Cable management for USB cable |
| Left Side | 24V DC Output | 2-pin 24V DC Jack with screw connector for Wincor iPOS x 1 |
| | 19V DC Output | 4-pin 19V DC output with lock connector for YUNO POS x 1 |
| | Cable Clamp | Cable management for USB cable |
| | USB IN port | USB port connect to YUNO POS / Wincor iPOS system via 3-in-1 cable |
| | LAN-A IN port | LAN port connect to YUNO POS / Wincor iPOS system via 3-in-1 cable |
| | USB-C Hold Bracket | Cable management for USB-C cable |
| | USB-C port | USB-C port connect to JAZZ / TWIST POS system via USB-C cable |
| Rear Side | Cash Drawer Voltage Setting | 3-pin pin-header x 2 |
| | COM Voltage Setting | 4-pin pin-header x 4 |
| Others | Power Supply | 100 ~ 240 V AC-in, 180 Watt 24V 7.5A DC-out adapter x 1 |
| | 1.8m 3-in-1 Cable (Optional) | Power cable (2-pin to 4-pin) x 1, LAN cable x 1 and USB cable x 1 |
| | 1.5m USB-C Cable (Optional) | USB-C cable x 1 |
| | Color / Material | Black Matte / SPCC |
| | Certification | CE, LVD, FCC and RCM |
| | Dimension | 300 x 125 x 43 mm (11.81 x 4.92 x 1.69 inches) |
| | Weight | 0.7 kg (1.54 lb.) |
| Environmental | Operating Temperature | -20 ~ 40°C (-4 ~ 104°F) |
| | Storage Temperature | -40 ~ 85°C (-40 ~ 185°F) |
| | Relative Humidity | 95% at 40°C (104°F), non-condensing |

*All trademarks and copyrights are the property of their respective owners.

**Content is subject to change without prior notice.

SAFETY INSTRUCTIONS

To disconnect the product from the electrical Power Supply, remove the power cable plug from the wall socket. The wall socket must be easily accessible and in close proximity to the product.

Read these instructions carefully. Save these instructions for future reference. Follow all warnings and instructions marked on the product.

Do not use this product near water.

Do not place this product on an unstable cart, stand, or table. The product may fall, causing serious damage to the product.

Only use power supply unit and cables released by AURES.

Do not allow anything to rest on the power cord. Do not locate this product where persons will walk on the cord.

Never spill liquid of any kind on the product.


WEEE Notice




The WEEE mark applies only to countries within the European Union (EU) and Norway.

This appliance is labeled in accordance with European Directive 2002/96/EC concerning waste electrical and electronic equipment (WEEE). The Directive determines the framework for the return and recycling of used appliances as applicable throughout the European Union. This label is applied to various products to indicate that the product is not to be thrown away, but rather reclaimed upon end of life per this Directive.

Front Side




Left Side



CAUTION : DO NOT connect the 180W power plug here.



Rear Side



| | | |
|--|---|---|
| <p>C/D Voltage Setting</p> <p>24V OUT 12V OUT</p> | <p>COM Voltage Setting</p> <p>N/A 5V OUT 12V OUT</p> | <p>Default setting :</p> <ul style="list-style-type: none"> ● Cash Drawer at 24V ● COM port at N/A <p>CAUTION : Turn the machine off before configuring the voltage setting</p> |
|--|---|---|

*Voltage Settings of Cash Drawer and COM ports are behind the service door.

Configure the voltage settings of Cash Drawer and each COM port if necessary.

How to mount?

Mount either at top or side with four included M3 screws.



Standard USB-C Hub is an innovative PoweredUSB Hub with extended I/O for YUNO / JAZZ / TWIST POS and Wincor iPOS, which allows you to enjoy versatile POS peripherals.

Features :

- Empower AURES YUNO POS and Wincor iPOS via foolproof design 3-in-1 cable (Power + LAN + USB) as well as AURES JAZZ and TWIST POS via USB Type C cable with PoweredUSB feature
- Power ON with connected POS
- Built-in microcontroller to provide standard COM port access
- Built-in cable clamp / hold bracket to avoid cable loosen
- Flexible mounting bracket to ease fixation

Serial Port Pin and Signal Assignments :

| Pin | Signal Name | Pin | Signal Name |
|-----|---------------------|-----|-----------------|
| 1 | Data Carrier Detect | 6 | Data Set Ready |
| 2 | Received Data | 7 | Request to Send |
| 3 | Transmitted Data | 8 | Clear to Send |
| 4 | Data Terminal Ready | 9 | Ring Indicator* |
| 5 | Signal Ground | | |

*Ring(Default) / +5V / +12V selected by jumper

Technical Support

The AURES Group thanks you for your loyalty.

To download our most recent drivers and utilities and obtain advice regarding the installation of your equipment, please visit the AURES Technical Support Website :

www.ares-support.fr/UK